

Таблица 5.16. Переносные свойства фреона 23 в однофазной области

p=0.1			p=1		p=5	
T	$\mu$	$\lambda$	$\mu$	$\lambda$	$\mu$	$\lambda$
233.15	1.154E-5	9.76E-3	1.650E-4	1.033E-1	1.741E-4	1.077E-1
253.15	1.254 E-5	1.084E-2	1.276E-5	1.286E-2	1.342E-4	9.35E-2
273.15	1.353 E-5	1.192 E-2	1.371 E-5	1.371 E-2	1.01E-4	7.97 E-2
293.15	1.450 E-5	1.301 E-2	1.466 E-5	1.463 E-2	6.36E-5	6.81 E-2
313.15	1.547 E-5	1.409 E-2	1.560 E-5	1.558 E-2	1.97 E-5	2.62 E-2
333.15	1.643 E-5	1.518 E-2	1.655 E-5	1.655 E-2	1.924 E-5	2.44 E-2
353.15	1.738 E-5	1.626 E-2	1.748 E-5	1.754 E-2	1.958 E-5	2.41 E-2
373.15	1.831 E-5	1.734 E-2	1.840 E-5	1.855 E-2	2.02 E-5	2.43 E-2
393.15	1.923 E-5	1.843 E-2	1.932 E-5	1.956 E-2	2.08 E-5	2.48 E-2
413.15	2.01 E-5	1.951 E-2	2.02 E-5	2.06 E-2	2.15 E-5	2.54 E-2
433.15	2.10 E-5	2.06 E-2	2.11 E-5	2.16 E-2	2.23 E-5	2.60 E-2
453.15	2.19 E-5	2.17 E-2	2.20 E-5	2.27 E-2	2.30 E-5	2.68 E-2
473.15	2.28 E-5	2.28 E-2	2.29 E-5	2.37 E-2	2.38 E-5	2.76 E-2
p=10			p=20			
233.15	1.847E-4	1.123E-1	2.050E-4	1.166E-1		
253.15	1.462E-4	9.90E-2	1.664E-4	1.046E-1		
273.15	1.159E-4	8.62 E-2	1.348E-4	9.34E-2		
293.15	8.58 E-5	7.86 E-2	1.119E-4	8.71 E-2		
313.15	6.03 E-5	6.65 E-2	8.91E-5	8.06 E-2		
333.15	3.99 E-5	5.03 E-2	7.12 E-5	7.35 E-2		
353.15	2.91 E-5	3.94 E-2	5.86 E-5	6.62 E-2		
373.15	2.60 E-5	3.52 E-2	4.97 E-5	5.95 E-2		
393.15	2.51 E-5	3.35 E-2	4.32 E-5	5.40 E-2		
413.15	2.50 E-5	3.27 E-2	3.88 E-5	5.00 E-2		
433.15	2.52 E-5	3.25 E-2	3.60 E-5	4.73 E-2		
453.15	2.56 E-5	3.26 E-2	3.43 E-5	4.55 E-2		
473.15	2.60 E-5	3.28 E-2	3.30 E-5	4.40 E-2		